

COUGAR



TX2-A



TX2-B

T60-Cougar Transmitter TX2-x	
Article number:	T60TX-15xML
Application areas:	Doors, entrances, gates, winches, pumps, crushers, lighting, conveyor belts, hydraulics a.o.
Frequency:	433,92 MHz
Mod. Type:	FSK
Coding:	Digital pulse code
Code comb.:	TX2-A: Adjustable codes; 59.049 (System 460: 27 or 81) Unique codes; 16.777.216 TX2-B: Adjustable codes; 59.049 (System 460: 6.561) Unique codes; 16.777.216
Functions:	TX2-A: 3 functions, possibility to remote up to 1000 objects TX2-B: 15 functions (System 460: 8 functions)
Output:	10 mW (by 50 ohm)
Antenna:	Built-in
Power supply:	Exchangeable 9 V battery type;6F22 (battery change once a year with normal use)
Power consumption:	TX2-A: Apr. 20 mA TX2-B: Apr. 26 mA
Temperature:	-20° C to +55° C
Weight:	Apr. 155 g incl. battery
Dimensions:	143 x 62 x 28 mm
Protection:	IP 65
Recommended receiver:	T60-Cougar receiver RX1-A and RX3-A with 1, 3, 4, 6 or 8 relays, T20/ T60-Cougar DIN and plug-in receiver (fully compatible with system 460).

N.L. Tucker & Associates Pty Ltd
12B Pitt Way
Booragoon, WA 6154
P: 08 9330 7911
F: 08 9317 1544
sales@nltucker.com.au

N.L. Tucker & Associates Pty Ltd
50 Marni Street
Dandenong South, Victoria 3175
P: 03 9706 6691
F: 03 9706 6692
vicsales@nltucker.com.au